



A38 SHIP TECHNICAL RIDER 2010

VENUE	A38 Ship - Budapest
ADDRESS	Pazmany Peter rakpart (Petofi Bridge Buda side) H-1117 Budapest
GPS	lat=47.476528, lon=19.06292
PHONE	0036 1 464 39 40
FAX	0036 1 464 39 45
WEBSITE	www.a38.hu
EMAIL	info at a38.hu

IMPORTANT NOTES

PROHIBITED	Use of pyrotechnics, confetti, silly strings of any kind.
SMOKING	Please note that per the XLII/1999., in Hungary, it is only allowed to smoke in clubs/pubs/restaurants and venues in assigned areas. (I.e. smoking is permitted on stage, in the concert hall etc.)
TIMESCHEDULE	Timeschedule will be sent by our production department. Please read and confirm. Due to legal aspects concerning the A38 staff working hours the agreed timeschedule is not to be exceeded. If set-up and soundcheck of the main act requires more time than 60 minutes, the hall expenses will go up 40 EUR per hour. Changes in get-in times and number of local crew cannot be accepted after one week prior to show because of finalizing planning schedules in due time.
LOCAL CREW	1x stagemanager 1x FOH engineer 1x Light engineer Monitor engineer and stagehands are an extra, please contact us!
SECURITY	Standard security / NO BARRIER
PARKING	Parking space is 60 meters. Tourbus-power connection 16 A.



STANDARD FACILITIES

DRESSING ROOMS	2 dressing rooms with shower and toilet
MERCHANDISE	We can provide merchandise desk (1,6mx1m), please contact us!
CATERING	A38 has it's own first class restaurant, we can provide hot meals and drinks there if agreed in advance. Please note that the restaurant is closed on Sundays. We serve drinks in the backstage bar.

TECHNICAL SPECS

MAX SOUND LEVEL	110 dBm (A) next to FOH mixer
STAGE	7,6 x 5,8 x 0,9 m (24,9 x 19 x 2,9 ft), or 11,6 x 5,8 x 0,9 m (38 x 19 x 2,9 ft). Heights above stage: 2,5 m (8,2 ft)
CONCERT HALL	Including stage: 11,6 x 25,8 x 4 m (38 x 84,6 x 13,12 ft). 3D view
POWER SUPPLY	Besides our usual power supply sound&light of house: 1x 3 phase 32 A on stage (lights), 1x3 phase 63A aft of ship (50m from stage) Backline power: 230V Transformer 2 pc 230V to 110V

STANDARD PA SPECS

FOH	Nexo Alpha sound system 2 pc Nexo Alpha M8-CF 2 pc Nexo Alpha M3-CF 4 pc Nexo Alpha B1-CF 4 pc Nexo Alpha S2-CF 3 pc Nexo Alpha NXAMP-4x4
FOH CONSOLE	1 pc Midas Verona 400, 32Ch / 8 Group / 8 Aux
FXS	1 pc Yamaha SPX 2000 1 pc Lexicon MPX-1 1 pc t.c. electronic M-One XL 3 pc dbx 1066 compressor 1 pc dbx 1046 compressor, limiter 2 pc BSS DPR-522 dual gate 1 pc BSS DPR 504 4 ch noise gate 1 pc Klark Technik DN 360 5 pc dbx 1231 EQ

Continues on next page >



MONITOR	We have 8 monitor ways and side fill 12 pc Nexo PS-15 3 pc Nexo NXAMP-4x1
MONITOR CONSOLE	1 pc Yamaha LS9/32
MICROPHONES	6 pc Shure Beta 58 4 pc Shure Beta 57 9 pc Shure SM 57 6 pc Shure SM58 2 pc Shure KSM 109 2 pc Shure Beta 52 1 pc Shure Beta 91 7 pc Sennheizer E-604 1 pc Shure ULXP2458+Sm58 4 pc Rode NT 5 MP 2 pc Audiotechnika AE3000 2 pc Beyerdynamic M88 3 db AKG C 418
RISER	6 pc 1x2 riser /to install 30cm, 60cm, 100cm height
OTHER	1 pc Soundcraft Folio E6 mixer 1 pc Tascam CD-RW 700 CD recorder 1 pc Tascam CD-01U pro CD player
FOR DJs	4 pc Technics MK II. 1210 turntable 2 pc Pioneer DJM-600 mixer 4 pc Pioneer CDJ-100 CD player

LIGHTS

MIXER	Avolites Pearl Expert
LAMPS	6 pc SGM 1200 intelligent lamps (scan) 48 pc PAR 64 1000W lamps 6 pc ETC Source Four Junior profil lamps 10 pc DTS Theatre fresnel 1000W 4 pc Balogh neon 18 pc Approx 4ch dimmer
OTHER	1 pc JEM ZR 33 smoke machine 1 pc Haser Loop Unic fog machine 1 pc mirror-ball (50cm) 1 pc Shark effect lamp
BACK DROP	Black curtain along the whole width of the stage

